

# Touch Sense Timed Exit Buttons

*The REX-TS Series Electric Pushbutton Switch*

**The REX-TS Series Electronic Pushbutton Switches** are a long-lasting control that provide a cost effective way to add time delay to a system.

## Features:

- Integrated Adjustable time delay allows for door opening time selection within the switch
- N.O. and N.C. outputs for maximum applicability
- Dual voltage means reduced inventory costs
- Adjustable Bi-LED brightness and color state (6 x 2 levels) for custom configuration
- Beeper sounds when relay activated to provide audible feedback to users

## Specifications:

**CURRENT DRAW:** 60mA~100mA/12V DC  
**SPDT RELAY RATING:** 3A/ 24VDC  
**TIME DELAY:** Adjustable from 1 to 30 seconds  
**OPERATING VOLTAGE:** 12~24 VDC  
**OPERATING TEMPER:** - 4 degrees F to 158 degrees F  
**FOR USE:** Indoor



**REX-TS-NS**



**REX-TS-SG**

Touch Sensitive - Narrow Stile Switch  
 Part# **REX-TS-NS**

Touch Sensitive - Single Gang Switch  
 Part# **REX-TS-SG**



The IP Lock and Security Company

2270 Camino Vida Roble  
 Carlsbad, CA 92011

Tel: 760-929-9596

Email: [Sales@BlueWaveSecurity.com](mailto:Sales@BlueWaveSecurity.com)

*Distributed by:*

CONTROLLER

SOFTWARE

CREDENTIAL  
READER

LOCKING  
DEVICE

REX SENSOR

ACCESSORIES